

Item	Device Type	CH	DALI Command (DALI#1 DALI#2)	Responses	Remarks
			(CMD DATA)	(DATA)	
Query Command:					
Query Device Type (查詢LED燈形態)	6	1	Lamp_ID*2+1 0x99	0x06 (indicated one channel)	
	8	?	Lamp_ID*2+1 0x99	0x08 (indicated multi-channel)	When the device type is 8, please use "Query Colour Type Features" command to determine the total of channel.
Query Colour Type Features	8	6	Lamp_ID*2+1 0xF9	0xD8 (indicated 6 channels)	
	8	2	Lamp_ID*2+1 0xF9	0x48 (indicated 2 channels)	
Query Actual Level (查詢單色燈亮度)	6	1	Lamp_ID*2+1 0xA0	Current Level	
	8	?	Lamp_ID*2+1 0xA0	0xFF (Color mode)	Update level for each channel
Query Colour Value (查詢顏色燈亮度)	8	6	0xA3 0x09 Lamp_ID*2+1 0xEA	Ch1 current Level	
			0xA3 0x0A Lamp_ID*2+1 0xEA	Ch2 current Level	
			0xA3 0x0B Lamp_ID*2+1 0xEA	Ch3 current Level	
			0xA3 0x0C Lamp_ID*2+1 0xEA	Ch4 current Level	
			0xA3 0x0D Lamp_ID*2+1 0xEA	Ch5 current Level	
			0xA3 0x0E Lamp_ID*2+1 0xEA	Ch6 current Level	
Dimming	6	1	Lamp_ID*2 0x00~0xFE		1-channel LED driver
	8	6	0xA3 0x3F Lamp_ID*2+1 0xED 0xA3 Ch1Level 0xC3 Ch2Level 0xC5 Ch3Level Lamp_ID*2+1 0xEB 0xA3 Ch4Level 0xC3 Ch5Level 0xC5 Ch6Level Lamp_ID*2+1 0xEC Lamp_ID*2+1 0xE2		6-channel LED driver
	8	2	0xA3 0x3F Lamp_ID*2+1 0xED 0xA3 Ch1Level 0xC3 Ch2Level Lamp_ID*2+1 0xEB Lamp_ID*2+1 0xE2		2-channel LED driver